

PHILIPS

Recessed

EvoKit LED Retrofit Kit Gen 4



Project: _____

Location: _____

Cat.No: _____

Type: _____

Lamps: _____ Qty: _____

Notes: _____

Philips EvoKit LED retrofit kit gen 4 is an energy efficient LED alternative to traditional linear fluorescent troffers. Not only does it offer energy savings¹, it also helps reduce maintenance costs due to its long lifetime. Simple construction helps decrease the installation time meaning you can have an LED solution in your ceiling in just minutes.

Ordering guide (continued on next page)

Product Number	12NC	Description	Watts ³	Volts	Lumen Maintenance (Hrs.) ²	Approx. Lumens ³	Color Temp. (K)	Efficacy	Diffusor
Dimming: 0-10V									
515692	929000781813	EvoKit 2x2 P 23L 17W 835 2 0-10 7 G4	17	120-277	70,000	2300	3500	134	Ribbed
515759	929000782213	EvoKit 2x2 P 23L 17W 840 2 0-10 7 G4	17	120-277	70,000	2300	4000	137	Ribbed
◆ 516005	929000783313	EvoKit 2x2 P 32L 24W 835 2 0-10 7 G4	24	120-277	70,000	3200	3500	132	Ribbed
◆ 515940	929000782713	EvoKit 2x2 P 32L 24W 840 2 0-10 7 G4	24	120-277	70,000	3200	4000	135	Ribbed
516237	929000785513	EvoKit 2x4 P 30L 22W 835 2 0-10 7 G4	22	120-277	70,000	3000	3500	135	Ribbed
516039	929000783613	EvoKit 2x4 P 30L 22W 840 2 0-10 7 G4	22	120-277	70,000	3000	4000	137	Ribbed
◆ 516286	929000786013	EvoKit 2x4 P 36L 27W 835 2 0-10 7 G4	27	120-277	70,000	3600	3500	135	Ribbed
◆ 516328	929000786413	EvoKit 2x4 P 36L 26W 840 2 0-10 7 G4	26	120-277	70,000	3600	4000	137	Ribbed
◆ 516427	929000787413	EvoKit 2x4 P 42L 32W 835 2 0-10 7 G4	32	120-277	70,000	4200	3500	134	Ribbed
◆ 516369	929000786813	EvoKit 2x4 P 42L 31W 840 2 0-10 7 G4	31	120-277	70,000	4200	4000	136	Ribbed
516534	929000788513	EvoKit 2x4 P 47L 36W 835 2 0-10 7 G4	36	120-277	70,000	4700	3500	132	Ribbed
516476	929000787913	EvoKit 2x4 P 47L 35W 840 2 0-10 7 G4	35	120-277	70,000	4700	4000	135	Ribbed
517482	929000798813	EvoKit 2x2 P 32L 24W 835 2 0-10 7 G4 SM	24	120-277	70,000	3200	3500	132	Smooth
517466	929000798613	EvoKit 2x2 P 32L 24W 840 2 0-10 7 G4 SM	24	120-277	70,000	3200	4000	135	Smooth
517508	929000799013	EvoKit 2x4 P 36L 27W 835 2 0-10 7 G4 SM	27	120-277	70,000	3600	3500	135	Smooth
517516	929000799113	EvoKit 2x4 P 36L 26W 840 2 0-10 7 G4 SM	26	120-277	70,000	3600	4000	137	Smooth
517540	929000799413	EvoKit 2x4 P 42L 32W 835 2 0-10 7 G4 SM	32	120-277	70,000	4200	3500	134	Smooth
517524	929000799213	EvoKit 2x4 P 42L 31W 840 2 0-10 7 G4 SM	31	120-277	70,000	4200	4000	136	Smooth

See footnotes on page 9.



EvoKit LED retrofit kit gen 4

Application

- A highly efficient, visually comfortable, architecturally styled LED retrofit kit designed to replace recessed linear fluorescent troffers.
- Unique modular design offers refreshing new look in the ceiling when compared to traditional fluorescent luminaires.
- Single light bar combined with slanted troffer helps reflect light to reduce glare and provide uniform light distribution making it ideal for applications such as offices, schools, healthcare and retail.
- Excellent color rendering with a CRI above 80.
- Extremely high efficacies up to 138 lumens per watt.
- LEDs are an excellent source for use with controls since dimming or frequent switching does not degrade the performance or life of the source.
- Designed for use with standard grid (NEMA "G") or Narrow Grid (NEMA "NFG") ceiling T-Grids.
- High efficiency source and luminaire design help significantly reduce energy consumption and more easily comply with known energy codes.
- Helps meet regulation requirements such as ASHRAE 90.1 and Title 24 when matched with suitable controls.

Construction/Finish

- Simple design allows for quick installation in existing luminaire without the need to break the ceiling plenum.

- Constructed using galvanized steel which helps fight rust and makes for more durable product.
- Integrated ceiling tabs for securement within the ceiling for areas prone to extreme conditions
- Minimum depth of only 3" necessary to allow proper clearance and installation of the EvoKit.
- Retrofit kit is powder coated after fabrication with high quality, durable finish to ensure no unfinished edges and avoid future potential of corrosion.
- Components fit together easily without the need for tools during installation.

Electrical

- Multiple driver options available
 - Philips Advance Xitanium SR driver allows flexibility to integrate a range of control options.
 - 0-10V dimming satisfies universal voltage requirements
- 5-year limited warranty includes all components of the retrofit kit, including driver, LED board and nonelectrical components.**
- Listed with UL and Design Lights Consortium† to ensure quality performance and safety standards are met.
- High efficiency LEDs have a minimum 70,000 hour rated life (L₇₀).

Enclosure

- Diffuser requires no frames or fasteners and can be easily removed from below without tools if needed.

Accessories

- Suitable for use with Philips 503441 emergency backup.
- Suitable for use with a wide range of control systems.
- Appropriate for new construction when used with standard listed lensed or parabolic troffers.

Prod. No.	Description
502583	EvoKit 2x4 replacement lens ribbed
517748	EvoKit 2x4 replacement lens smooth
502575	EvoKit 2x2 replacement lens ribbed
517755	EvoKit 2x2 replacement lens smooth
503441	EvoKit field installed emergency battery backup (requires the use of bracket)
517730	EvoKit emergency battery backup bracket (brackets come in packs of 4)

EvoKit with new SimpleSet technology for wireless lumen level programming

EvoKit with new SimpleSet technology allows the maximum lumen level to be set prior to installation using a smartphone-based app without requiring power to the luminaire. Available in the 0-10V and SR versions only. The app can be downloaded at Google Play. Please contact your Philips representative for the current list of approved Android smartphones. Distributors can set lumen levels prior to shipping, and contractors can set lumen levels prior to installation. Lumen level is quickly and easily set in two steps:



Step 1: Place the smartphone next to the NFC antenna on the driver.

Step 2: Follow the on-screen instructions.

