

Presented By: Candela Corporation
Contact Phone: (800) 922-9226
Contact E-mail: sales@candelacorp.com

Customer Name:
Project Name:
Fixture Type:





GE
Lighting

72269 - GE-132-MV-N

GE LFL Multi-Volt ProLine™ Electronic Multivolt Instant Start Ballast

- High performance electronic ballast for all general fluorescent applications
- Instant start electronic ballast for long lamp starting cycles and low initial cost
- Multi-Voltage Technology handles voltage from 120 to 277V
- Light-weight, Low Profile Housing
- Parallel lamp operation means system maintenance is easier to manage



GENERAL CHARACTERISTICS

Application	1- F32T8 120 to 277 "N".87 BF
Category	Linear Fluorescent
Ballast Type	Electronic - Multivolt Instant Start
Starting Method	Instant start
Lamp Wiring	Parallel
Line Voltage Regulation (+/-)	10 %
Case Temperature	70 °C(158 °F)
Ballast Factor	Normal
Power Factor Correction	Active
Sound Rating	A (20-24 decibels)
Additional Info	Auto-restart/Thermally protected

PRODUCT INFORMATION

Product Code	72269
Description	GE-132-MV-N
Standard Package	Case
Standard Package GTIN	10043168722695
Standard Package Quantity	10
Sales Unit	Standard Pack
No Of Items Per Sales Unit	1
No Of Items Per Standard	10
Package	
UPC	043168722698

DIMENSIONS

Case dimensions			
Length (L)			9.5 in(241.30 mm)
Width (W)			1.3 in(33.02 mm)
Height (H)			1.2 in(29.97 mm)
Mounting dimensions			
Mount Length (M)			8.9 in(226.06 mm)
Mount Width (X or F)			1.1 in(27.94 mm)
Mount Slots (MS)			0.3 in(7.62 mm)
Weight			1.4 lb
Exit Type			Side
Remote Mounting Distance to Lamp			18 ft
Remote Mounting Wire Gauge			18 AWG
Lead lengths	Qty	Exit	Length (± 1 in.)
Black	1	Left	25 (635mm)
Blue	1	Right	31 (787mm)
Red	1	Right	45 (1143mm)
White	1	Left	25 (635mm)

ELECTRICAL CHARACTERISTICS

Supply Current Frequency	50 Hz/60 Hz
--------------------------	-------------

SAFETY & PERFORMANCE

- cUL Listed
- FCC - CLASS A Non-Consumer
- UL Class P
- UL Listed
- UL Type 1 Outdoor
- UL Type HL
- RoHS Compliant
- NEMA Premium®

SPECIFICATIONS BY LAMP & WATTAGE

Lamp	# of Lamps	Line Volts	System Watts	Nom. Line Current	System Ballast Factor	Ballast Efficacy Factor	Power Factor% (>=)	Crest Factor THD% (<=)	Min. Starting Temp (°F/°C)
F32T8/WM	1	120	26	0.22 A	0.88	3.38	99	1.7 6	60.0 / 16
F32T8/WM	1	277	26	0.1 A	0.88	3.38	96	1.7 8	60.0 / 16
F32T8/25W	1	120	24	0.0 A	0.88	3.67	99	1 1/2 10	60.0 / 16
F32T8/25W	1	277	24	0.0 A	0.88	3.67	97	1 1/2 10	60.0 / 16
F32T8	1	120	28	0.23 A	0.87	3.11	99	1.7 6	0.0 / -18
F32T8	1	277	28	0.1 A	0.87	3.11	96	1.7 8	0.0 / -18
F28T8	1	120	25	0.21 A	0.88	3.52	99	1.7 6	60.0 / 16
F28T8	1	277	25	0.09 A	0.88	3.52	95	1.7 9	60.0 / 16
F25T8	1	120	22	0.19 A	0.93	4.23	99	1.7 7	0.0 / -18

F25T8	1	277	23	0.09 A	0.93	4.04	94	1.7	9	0.0 / -18
F17T8	1	120	16	0.14 A	0.92	NaN	99	1.7	9	0.0 / -18
F17T8	1	277	16	0.07 A	0.92	NaN	84	1.7	11	0.0 / -18

CAUTIONS & WARNINGS

Warning

- Risk of Electric Shock
 - Properly ground ballast and fixture.
 - Turn power off before servicing--see instructions.

WARRANTY INFORMATION

GE Lighting warrants to the purchaser that each ballast will be free from defects in material or workmanship for period as defined in the attached documents from the date of manufacture when properly installed and under normal conditions of use.