

TRACK CONNECTORS

120V Track System

WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

Track Connectors		Model		Finish	Description
Live End Connector		HLE H Track LLE L Track JLE J Track J2-LE J2 Track	4¼" × 1⅜" × ¾" 4¼" × 1⅜" × ¾" 4¾" × 1¼" × ¾" 4¾" × 1¼" × ¾"	BK Black BN* Brushed Nickel WT White DB** Dark Bronze	Use for direct wiring through ceiling. A canopy plate is required when using with a standard junction box.
Live End BX Connector		HBXLE H Track LBXLE L Track JBXLE J Track J2-BXLE J2 Track	6" × 1⅜" × 1¼" 5¾" × 1⅜" × 1¼" 6¼" × 1⅜" × 1¼" 5⅞" × 1⅜" × 1¼"		Use with surface mounted BX or non-metallic sheathed cable. Also provides through the ceiling connection.
"I" Power Connector		HI-PWR H Track LI-PWR L Track JI-PWR J Track J2-IPWR J2 Track	6¾" × 1⅜" × ¾" 7" × 1⅜" × ¾" 7⅞" × 1⅜" × ¾" 7" × 1⅜" × ¾"		Power entry point at the connection of 2 tracks.
"L" Connector Left		HL-LEFT H Track LL-LEFT L Track JL-LEFT J Track J2-LLEFT J2 Track	2¾" × 2¾" × ¾" 4¼" × 4¼" × ¾" 4¼" × 4¼" × ¾" 4¼" × 4¼" × ¾"		Use to join 2 track sections to make power feedable 90° left polarity turns.
"L" Connector Right		HL-RIGHT H Track LL-RIGHT L Track JL-RIGHT J Track J2-LRIGHT J2 Track	2¾" × 2¾" × ¾" 4¼" × 4¼" × ¾" 4¼" × 4¼" × ¾" 4¼" × 4¼" × ¾"		Use to join 2 track sections to make power feedable 90° right polarity turns.
"T" Connector		HT H Track LT L Track JT J Track J2-T J2 Track	4" × 2¾" × ¾" 7¼" × 4¼" × ¾" 7⅞" × 4¼" × ¾" 7" × 4¼" × ¾"		Use to join 3 track sections. Power feedable on H and J only. "T" Connector with opposite polarity can be custom ordered.
"X" Connector		HX H Track LX L Track JX J Track J2-X J2 Track	4⅞" × 4⅞" × ¾" 7⅞" × 7⅞" × ¾" 7⅞" × 7⅞" × ¾" 7" × 7" × ¾"		Use to join 4 track sections. Power feedable on H and J only.
"I" Connector		HI H Track LI L Track JI J Track J2-I J2 Track	3" × 1⅜" × ¾" 3⅞" × 1⅜" × ¾" 3" × 1⅜" × ¾" 4½" × 1⅜" × ¾"		Use to join two sections of track with electrical continuity.
"I" Dead End Connector		HI-DEC H Track LI-DEC L Track JI-DEC J Track J2-IDEC J2 Track	3" × 1⅜" × ¾" 3⅞" × 1⅜" × ¾" 3" × 1⅜" × ¾" 3½" × 1⅜" × ¾"		Joins two sections of track without electrical continuity.
Flexible Track Connector		HFLX H Track LFLX L Track JFLX J Track J2-FLX J2 Track	11" × 1⅜" × ¾" 9¾" × 1⅜" × ¾" 8½" × 1⅜" × ¾" 11½" × 1⅜" × ¾"		Connects two track sections at variable angles. Use as a transition from wall-to-wall, wall-to-ceiling, or ceiling-to-ceiling. Power feedable.
Floating Canopy Connector		HFC H Track LFC L Track JFC J Track	4½" × 4½" × 1½" 4¼" × 4¼" × 1⅜" 4⅝" × 4⅝" × 1⅜"		Connects to octagon box. Allows track to be powered anywhere along the length of the track.

*BN finish only available for H, L, J Track **DB finish only available for H Track

WAC Lighting

www.waclighting.com

Phone (800) 526.2588 • Fax (800) 526.2585

Headquarters/Eastern Distribution Center

44 Harbor Park Drive • Port Washington, NY 11050

Phone (516) 515.5000 • Fax (516) 515.5050

Western Distribution Center

1750 Archibald Avenue • Ontario, CA 91760

Phone (800) 526.2588 • Fax (800) 526.2585