

## AVAILABLE MODELS

ORDER	ORDER CODE	ITEM #	LENGTH	WATTS**	CCT***	LUMENS	EFFICACY (lm/W)	VOLTAGE	TRADITIONAL WATTAGE EQUIVALENT
	13810	LS3-103-FCCT*	10"	3W	27/30/35/40/5000K	330 lm	110 lm/W	120V	9" 6W T5
	13811	LS3-145-FCCT*	14"	5W	27/30/35/40/5000K	550 lm	110 lm/W	120V	12" 8W T5
	13812	LS3-PS239-FCCT*	23"	9/7/5W	27/30/35/40/5000K	990/770/550 lm	110 lm/W	120V	22" 14W T5 HE
	13813	LS3-PS3514-FCCT*	35"	14/12/10W	27/30/35/40/5000K	1540/1320/1100 lm	110 lm/W	120V	34" 21W T5 HE
	13814	LS3-PS4718-FCCT*	47"	18/15/12W	27/30/35/40/5000K	1980/1650/1320 lm	110 lm/W	120V	46" 28W T5 HE

\* Requires LS3-JB, LS3-JBS, LS3-PC6 for power

\*\* All power-selectable fixtures ship at the highest wattage setting

\*\*\* All CCT-selectable fixtures ship at 5000K

MODEL CONFIGURATOR					
MODEL	-	LENGTH	WATTS	-	CCT
LS3	-			-	

EXAMPLE PART NUMBER: PART NUMBER FROM AVAILABLE MODELS

REFER TO FOLLOWING SECTIONS FOR DETAILS ON FACTORY INSTALLED OPTIONS & AVAILABLE FIELD INSTALLED OPTIONS

## ACCESSORIES

ORDER	ORDER CODE	ITEM #	DESCRIPTION
<b>MOUNTING &amp; PROTECTION ACCESSORIES</b>			
	14237	LS3-CON06	6" Interconnect wire for LS2 and LS3 
	14239	LS3-CON12	12" Interconnect wire for LS2 and LS3 
	14238	LS3-CON36	36" Interconnect wire for LS2 and LS3 
	14240	LS2-JB*	Junction box for LS2 and LS3, 120VAC 
	14241	LS3-JBS*	Junction box with switch for LS2 and LS3 120VAC 
	14242	LS3-MAGCLIP	Magnetic clips for LS2 and LS3 
	14243	LS3-MAGCLIP-90	Magnetic clips with 90° elbow for LS2 and LS3 
	14245	LS3-PC6*	72" Power cord for LS2 and LS3, 120VAC 

\* **NOTE:** LS2-JB, LS3-JBS or LS3-PC6 required to power LS3 fixtures