



Product Number: 47364

Order Abbreviation: LU400/MULTI-KIT

General Description: 120/208/240/277V multi-tap magnetic core and coil ballast for 400W high pressure sodium lamp

Product Information

Abbrev. With Packaging Info.	LU400MULTIKIT 1/CS 1/SKU
ANSI Code	S51
Ballast Factor	1
Ballast Height H (in)	4.0000
Ballast Length L (in)	4.7500
Ballast Width W (in)	4.2500
Capacitor Diameter	1.75
Capacitor Height	5"
Circuit Type	CWA
Input Current (Amps)	0.00
Nominal Voltage (V)	120/208/240/277V
Number of Lamps	1
Open Circuit Voltage (V)	190
Power Factor	>0.9
Primary Lamp Type	LU400
Sound Rating	N
Starting Method	PULSE IGNITOR
Starting Temperature - Fahrenheit	-40°F
Starting Temperature - Celsius	-40°C
Total Harmonic Distortion (THD)	<20%
Wiring Method	LEADS
Total Maximum Wattage	464



Footnotes

- Product is a kit containing the core & coil, capacitor, ignitor (where required), brackets and mounting hardware
- Install in accordance with National Electric Codes
- High Voltage Pulse Present on Open Circuit
- Ground Ballast Core and Metallic Case of Capacitor and Ignitor
- Minimum Starting Temperature: -40F/-40C.
- Product contains installation instructions