











60W Lighting Transformer

Indoor & Outdoor AC Magnetic Class 2 Lighting Transformer

Product Code: M60L12-AR

Magnitude's M60L12-AR is the most compact lighting transformer on the market with a magnetic transformer core. It is equipped with two auto-reset breakers, one on the input and one on the output, which protect both the load and transformer. The transformer is encased in a coated metal box that includes 2 knock-outs, one on each side, to enable easy installation that complies with electrical code requirements.

Features


Dimmable with any standard MLVTRIAC dimmer Two auto-reset circuit breakers ETL listed Certified to CSA Standard Class 2 Commercial and Residential Use


Nema 3R enclosure

Wiring compartment with 2 knock-outs for clean and easy installation.









Specifications

| Max Load | 60W |
|---|--|
| Input Voltage | 120V AC |
| Input Current Full Load | 0.54 A |
| Output Voltage Full Load | 11.5V AC |
| Max Output Current Full Load | 4.8A |
| Open Circuit Output Voltage | 12.5V AC |
| Efficiency on I | 89.2% |
| Coil Former | Double Section Bobbin |
| Max. Ambient Temperature | -30°C to 50°C |
| Min. Installation Space Between Drivers | 5"Inch |
| Thermal Class | B130°C |
| Leads Primary | PVC 600V #20 |
| Leads Secondary | PVC 300V #16 |
| Circuit Breaker | primary and secondary auto reset |
| Dimensions L*W*H | 6.55 in. x 2.25 in. x 2.55 in. (166.3 mm x 57.15 mm x 64.7 mm) |
| Weight | 50 Oz. |

The specifications are subject to change without notice