



| Model No.       | VE126120MR    |
|-----------------|---------------|
| Family          | Stratus       |
| Ballast Type    | Electronic    |
| Lamp Operation  | Parallel      |
| Input Voltage   | 120V          |
| Starting Method | Program Start |

## PRODUCT SPECIFICATION

## ELECTRONIC BALLASTS

| Lamp Type     | No. of Lamps | Input Voltage (V) | Input Current (A) | Input Power (W) | Power Factor | MAX THD (%) | Ballast Factor | Min. Starting Temp.(F/C) | Lamp Current Crest Factor | B.E.F. |
|---------------|--------------|-------------------|-------------------|-----------------|--------------|-------------|----------------|--------------------------|---------------------------|--------|
| CFTR26W/GX24q | 1            | 120               | 0.50              | 26              | 0.50         | 150         | 0.92           | 0                        | 1.7                       | 3.54   |
| CFQ26W/G24q   | 1            | 120               | 0.50              | 26              | 0.50         | 150         | 0.92           | 0                        | 1.7                       | 3.54   |

## Physical Parameters

| Enclosure (in) | Lead Length in.(+/-1.0) |
|----------------|-------------------------|
| Length         | 3.90                    |
| Width          | 2.0                     |
| Height         | 1.2                     |
| Mounting       | 3.50                    |
|                | Black                   |
|                | White                   |
|                | Red                     |
|                | Blue                    |
|                | Yellow                  |

## Wiring Diagram

